

# **sLED**

by **Switch Lighting**



**SL50-30-W**

Wide angle lighting



**SL55-30-W**

Wide angle lighting






**SL56-30-W**

Wide angle lighting

# Downlight

Lighting excellence for every space.

- + 80% energy savings
- + dimming
- + fully sealed – IP44
- + 5 year warranty



## Beam control

**Diffuser**  
Opaque

**Beam angle**



90°

## Other options

**Trim colour**



White



Black  
SL50 only

## CCT options

**CRI**  
80

**CCT**



3000K



4000K  
SL50 only

## Product information

(example: 3000K)

| Model | Power (W) | Delivered lumens (lm) | Insulation Coverable |     |       |
|-------|-----------|-----------------------|----------------------|-----|-------|
|       |           |                       | NZ                   | AU  | UK/EU |
| SL50  | 8.6       | 840                   | ICF                  | IC4 | ✓     |
| SL55  | 12.8      | 1250                  | ICF                  | IC4 | ✓     |
| SL56  | 12.8      | 1250                  | ICF                  | IC4 | ✓     |

|             |               |                    |                  |       |
|-------------|---------------|--------------------|------------------|-------|
| <b>SL50</b> |               |                    |                  |       |
|             | Size 103x42mm | Cut-out Ø89-92mm   | Hole depth >45mm | Front |
| <b>SL55</b> |               |                    |                  |       |
|             | Size 120x42mm | Cut-out Ø98-108mm  | Hole depth >45mm | Front |
| <b>SL56</b> |               |                    |                  |       |
|             | Size 150x42mm | Cut-out Ø122-135mm | Hole depth >45mm | Front |

## how to specify sLED Downlight

e.g. code = SL50-30-W

| Model | CCT         | Trim Colour |
|-------|-------------|-------------|
| SL50  | 30 = 3000K  | W = White   |
| SL55  | 40 = 4000K* | B = Black*  |
| SL56  |             |             |

\*Option only available in SL50.

Please see [www.switch-lighting.co.nz](http://www.switch-lighting.co.nz) for full specifications, lux levels, SDoCs, ies files and installation instructions.

Warranty  
5 Years

